


| | |
|------|-------|
| CAT: | FEET: |
|------|-------|

| | |
|-------|----------|
| TYPE: | PROJECT: |
|-------|----------|



Aisle lighting edge delineation system is Patented, field-cutttable, co-extruded, rigid and soft PVC with Titanium Series LED lighting engine.

Features

- Individually replaceable LED PCB's snap into Titanium modules for easy and economical maintenance.
- Impervious to water and includes an integral seal for each end.

Mounting

Base installed using glue and screws for durability with snap on lens.

Applications

Illuminated walkway edge delineation system for theaters and auditoriums.

Warranty

5 years



Technical Information



| Profiles | Carpet-to-Edge (CE), Carpet-to-wall (CW) Carpet-to-Carpet (CC) | | | |
|-------------------|--|--------|--------|--------|
| | 4" | 6" | 12" | 18" |
| LED Spacing O.C. | 4" | 6" | 12" | 18" |
| *Watts/ft | 0.0036 | 0.0024 | 0.0012 | 0.0008 |
| CRI | > 80/TYP83 | | | |
| Kelvin Temp | 1900K, 2700K, 3000K, 3500K, 4000K, (+/-80K) SDCM Red, Blue, Amber | | | |
| Rated Life | 75,000 hrs. | | | |
| Max Run Length | 120ft./<1W | | | |
| Order Increments | 4', 8' | | | |
| Operating Voltage | 12V DC | | | |
| Power Supply | Class 2 | | | |
| Dimmable | Yes | | | |

*Based on 3000K

Profile Dimensions



Recommended Power Supplies

ADUL - NON DIMMING

| DESCRIPTION | CAT NO | APPLICATION | PRIMARY VOLTAGE | SECONDARY VOLTAGE | CIRCUIT BREAKERS | MAX LOAD | CIRCUIT CAPACITY |
|---------------------------------------|-------------------|------------------|------------------------|-------------------|------------------|----------|------------------|
| ADUL Series Class 2 Transformer | ADUL-80-1-5-12-D | Indoor / Damp | 100-277V AC 5ø60 HZ | 12V DC | 1 | 60W | 5A |
| | ADUL-150-2-5-12-D | | | | 2 | 2x60W | 2x5A |
| | ADUL-240-3-5-12-D | | | | 3 | 3x60W | 3x5A |
| | ADUL-320-4-5-12-D | | | | 4 | 4x60W | 4x5A |

ADUL - 0-10V DIMMING

| DESCRIPTION | CAT NO | APPLICATION | PRIMARY VOLTAGE | SECONDARY VOLTAGE | CIRCUIT BREAKERS | MAX LOAD | CIRCUIT CAPACITY |
|---------------------------------------|---------------------|------------------|------------------------|-------------------|------------------|----------|------------------|
| ADUL Series Class 2 Transformer | ADUL-80-1-5-12-DOT | Indoor / Damp | 100-277V AC 5ø60 HZ | 12V DC | 1 | 60W | 5A |
| | ADUL-150-2-5-12-DOT | | | | 2 | 2x60W | 2x5A |
| | ADUL-240-3-5-12-DOT | | | | 3 | 3x60W | 3x5A |
| | ADUL-320-4-5-12-DOT | | | | 4 | 4x60W | 4x5A |

ADUL - DMX SINGLE ADDRESS

| DESCRIPTION | CAT NO | APPLICATION | PRIMARY VOLTAGE | SECONDARY VOLTAGE | CIRCUIT BREAKERS | MAX LOAD | CIRCUIT CAPACITY |
|---------------------------------------|---------------------|------------------|------------------------|-------------------|------------------|----------|------------------|
| ADUL Series Class 2 Transformer | ADUL-80-1-5-12-DIN | Indoor / Damp | 100-277V AC 5ø60 Hz | 12V DC | 1 | 60W | 5A |
| | ADUL-150-2-5-12-DIN | | | | 2 | 2x60W | 2x5A |
| | ADUL-240-3-5-12-DIN | | | | 3 | 3x60W | 3x5A |

ADUL - DMX MULTI ADDRESS

| DESCRIPTION | CAT NO | APPLICATION | PRIMARY VOLTAGE | SECONDARY VOLTAGE | CIRCUIT BREAKERS | MAX LOAD | CIRCUIT CAPACITY |
|---------------------------------------|-----------------------|------------------|------------------------|-------------------|------------------|----------|------------------|
| ADUL Series Class 2 Transformer | ADUL-150-2-5-12-DIN-2 | Indoor / Damp | 100-277V AC 5ø60 Hz | 12V DC | 2 | 2x60W | 2x5A |
| | ADUL-240-3-5-12-DIN-3 | | | | 3 | 3x60W | 3x5A |
| | ADUL-320-4-5-12-DIN-4 | | | | 4 | 4x60W | 4x5A |

INFINITY - MLV / ELV / 0-10V / PWM / TRIAC

| DESCRIPTION | CAT NO | APPLICATION | PRIMARY VOLTAGE | SECONDARY VOLTAGE | CIRCUIT BREAKERS | MAX LOAD | MIN LOAD | CIRCUIT CAPACITY |
|---|-------------------|---------------------|-----------------|-------------------|------------------|----------|----------|------------------|
| Infinity Series Class 2 Transformer | INF-J-30-1-2.5-12 | Indoor / Outdoor | 100 - 277V AC | 12VDC | 1 | 30W | 3W | 2.5A |
| | INF-J-60-1-5-12 | | | | 1 | 60W | 6W | 5A |
| | INF-J-180-3-5-12 | | | | 3 | 3x60W | 3x6W | 3x5A |
| | INF-J-300-5-5-12 | | | | 5 | 5x60W | 5x6W | 5x5A |

Recommended Dimmers

DIMMING - 0-10V

| DESCRIPTION | CAT NO | APPLICATION | INPUT VOLTAGE | OUTPUT VOLTAGE | MAX LOAD |
|--------------|------------|-------------|---------------|----------------|-------------------------------|
| 0-10V Dimmer | DIM-LD-010 | Indoor | 12V/24V DC | 12V/24V DC | 30 mA max. output (sink only) |

DIMMING - MLV


| DESCRIPTION | CAT NO | APPLICATION | INPUT VOLTAGE | OUTPUT VOLTAGE | MAX LOAD |
|-------------|--------|-------------|---------------|----------------|----------|
| MLV Dimmer | N-600 | Indoor | 120V AC | 120V AC | 450W |
| | N-1000 | | | | 800W |
| | N-1500 | | | | 1200W |
| | D-600 | | | | 450W |
| | M-600 | | | | 450W |
| | M-1000 | | | | 800W |

DIMMING - ELV

| DESCRIPTION | CAT NO | APPLICATION | INPUT VOLTAGE | OUTPUT VOLTAGE | MAX LOAD |
|-------------|--------|-------------|---------------|----------------|----------|
| ELV Dimmer | ME-600 | Indoor | 120V AC | 120V AC | 450W |
| | DE-300 | | | | 300W |


DIMMING - DMX

| DESCRIPTION | CAT NO | APPLICATION | INPUT VOLTAGE | OUTPUT PROTOCOL | MAX UNIVERSE |
|----------------|--------------|-------------|---------------|-----------------|--------------|
| DMX Controller | TVOQ-1-WH | Indoor | 5V DC | DMX 512 | 1 |
| | TVOQ-2-BK | | 6V DC | | |
| | TVOQ-2-WH | | | | |
| | TVOQ-10-BK-7 | | 6-7V DC | | 2 |
| | TVOQ-10-WH-7 | | | | |




Touchscreen

TVOQ-1-WH
WH (White only)



Touchscreen

TVOQ-10-XX-7
XX = BK (Black), WH (White)




Touchscreen

TVOQ-2-XX
XX = BK (Black), WH (White)

Ordering Information


| PRODUCT CODE | PROFILE | LED COLOR | SPACING | LENS | LENGTH |
|----------------------------|---|---|--|-------------------------|----------------------|
| SATT | | | | | |
| SATT = Soft Aisle Titanium | CC = Carpet to Carpet CW = Carpet to Wall CE = Carpet to Edge | 19 = 1900K 27 = 2700K 30 = 3000K 35 = 3500K 40 = 4000K AM = Amber RD = Red BL = Blue | 04 = 4" 06 = 6" 12 = 12" 18 = 18" | C = Clear B = Bronze | 4.0 = 4' 8.0 = 8' |

Accessories - Extrusion End Caps




SATT-CW-CC-EC-06
L/R Carpet to Wall/Carpet To Carpet End Cap Assembly - Includes 6" pre-mitered extrusion with End Cap installed. Works for left or right. Clear Lens.

SATT-CW-CC-EC-06-B
Same as above with Bronze Lens



SATT-CE-LS-EC-06
Left End Cap Assembly, Carpet to Edge - Includes 6" pre-mitered extrusion with Left End Cap installed. Clear Lens.


SATT-CE-LS-EC-06-B
Same as above with Bronze Lens.




SATT-CE-RS-EC-06
Right End Cap Assembly, Carpet to Edge - Includes 6" pre-mitered extrusion with Right End Cap installed. Clear Lens.

SATT-CE-RS-EC-06-B
Same as above with Bronze Lens.


Mounting Accessories



SATT-LNS-SEALS
Replaceable lens seam seals



JBOX-LP
Junction box, low profile




BS-CC-8
Wall wireway, 8' Black Base & Conduit Cover




BSL-PC-1/4
1/4" Flex Conduit, Black

Replacement Parts




REPLACEMENT LED PCB

- TT-LED-19**
1900K
- TT-LED-27**
2700K
- TT-LED-30**
3000K
- TT-LED-35**
3500K
- TT-LED-40**
4000K
- TT-LED-AM**
Amber
- TT-LED-BL**
Blue
- TT-LED-RD**
Red




4" O.C. REPLACEMENT STRAND WITH LED

- SATT-04-STRAND-XX**
Available in XX = 19/27/30/35/40
- SATT-04-STRAND-RD**
Replacement Strand with Red LED
- SATT-04-STRAND-BL**
Replacement Strand with Blue LED
- SATT-04-STRAND-AM**
Replacement Strand with Amber LED




6" O.C. REPLACEMENT STRAND WITH LED

- SATT-06-STRAND-XX**
Available in XX = 19/27/30/35/40
- SATT-06-STRAND-RD**
Replacement Strand with Red LED
- SATT-06-STRAND-BL**
Replacement Strand with Blue LED
- SATT-06-STRAND-AM**
Replacement Strand with Amber LED




12" O.C. REPLACEMENT STRAND WITH LED

- SATT-12-STRAND-XX**
Available in XX = 19/27/30/35/40
- SATT-12-STRAND-RD**
Replacement Strand with Red LED
- SATT-12-STRAND-BL**
Replacement Strand with Blue LED
- SATT-12-STRAND-AM**
Replacement Strand with Amber LED




18" O.C. REPLACEMENT STRAND WITH LED


- SATT-18-STRAND-XX**
Available in XX = 19/27/30/35/40
- SATT-18-STRAND-RD**
Replacement Strand with Red LED
- SATT-18-STRAND-BL**
Replacement Strand with Blue LED
- SATT-18-STRAND-AM**
Replacement Strand with Amber LED




- WW-CC-BK-8**
Carpet to Carpet Base Black and Cover 8' Black
- WW-CC-GY-8**
Carpet to Carpet Base Black and Cover 8' Grey
- WW-CW-BK-8**
Carpet to Wall Base Black and Cover 8' Black
- WW-CW-GY-8**
Carpet to Wall Base Black and Cover 8' Grey
- WW-CW-BS-8**
Base Only, Carpet to Wall, Black, 8'
- WW-CC-BS-8**
Base Only, Carpet to Carpet, Black, 8'
- WW-TC-CL-8**
Lens Cover Only, Clear, 8'
- WW-TC-BK-8**
Lens Cover Only, Black, 8'
- WW-TC-BZ-8**
Lens Cover Only, Bronze, 8'
- WW-TC-GY-8**
Lens Cover Only, Gray, 8'



- WW-CE-BK-8**
Carpet to Edge Base Black and Cover 8' Black
- WW-CE-GY-8**
Carpet to Edge Base Black and Cover 8' Gray
- WW-CE-BS-8**
Base Only, Black Carpet To Edge, Black, 8'
- WW-TC-CL-8**
Lens Cover Only, Clear, 8'
- WW-TC-BK-8**
Lens Cover Only, Black, 8'
- WW-TC-BZ-8**
Lens Cover Only, Bronze, 8'
- WW-TC-GY-8**
Lens Cover Only, Gray, 8'




Floor to Floor Application add
BNS-TT-R-12



BS-CC-8
Wall wireway, 8' Black Base & Conduit Cover

Two Tone Bullnose Accessories




BNS-TT-R-12
Step Reducer, 12' Section



- ADH-MB-75AM-10**
Extrusion adhesive, 10.1 oz tubes, sold individually. 30 per case.
- ADH-MB-75AM-29**
Extrusion adhesive, 29 oz tubes, sold individually. 12 per case.



- ADH-IA-10.2-CA**
End Cap Adhesive, Clear liquid adhesive for end caps. 10.2 oz tubes sold individually in case of 12 each.



TM-3/16
Concrete Screw 3/16" x 1 3/4"



RONDB-1/8
Concrete Drill Bit 1/8" nail.